Approximation of linear distributed parameter systems by delay systems

Michaël Di Loreto, Sérine Damak, Damien Eberard, Xavier Brun

► To cite this version:

Michaël Di Loreto, Sérine Damak, Damien Eberard, Xavier Brun. Approximation of linear distributed parameter systems by delay systems. *Automatica*, 2016, 68, pp.162-168. 10.1016/j.automatica.2016.01.065 . hal-01281589

HAL Id: hal-01281589

<https://hal.science/hal-01281589>

Submitted on 24 Apr 2019

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Distributed under a Creative Commons Attribution - NonCommercial - NoDerivatives| 4.0
International License

Approximation of linear distributed parameter systems by delay systems[★]

Michaël Di Loreto^a, Sérine Damak^a, Damien Eberard^a, Xavier Brun^a

^a *Université de Lyon, Laboratoire Ampère, INSA-Lyon, 20 Avenue Albert Einstein, Villeurbanne 69621, France*

Abstract

The present work addresses continuous-time approximation of distributed parameter systems governed by linear one-dimensional partial differential equations. While approximation is usually realized by lumped systems, that is finite dimensional systems, we propose to approximate the plant by a time-delay system. Within the graph topology, we prove that, if the plant admits a coprime factorization in the algebra of BIBO-stable systems, any linear distributed parameter plant can be approximated by a time-delay system, governed by coupled differential-difference equations. Considerations on stabilization and state-space realization are carried out. A numerical method for constructive approximation is also proposed and illustrated.

Key words: Distributed parameter systems, time-delay systems, approximation, stabilization

---

1 Introduction

In the input-output approach, approximating a plant means to find a more tractable model with respect to given specifications for analysis, simulation and control synthesis. For distributed parameter plants governed by linear 1-D partial differential equations [5,8,38,4], approximation is, in general, realized by lumped models described by linear ordinary differential equations [25]. In feedback and interconnection perspectives, the graph topology of input-output systems, introduced in [33,34] to handle a topology where feedback is a robust property, gives a supporting structure for approximation. See also [37,27,22,2] for generalizations and metrics of the graph topology for distributed parameter plants. Approximation by lumped models in the graph topology was formalized in [35], and studied further in [23,24,26] for various metrics. A preliminary result in lumped stabilization for time-delay systems, viewed as a subclass of distributed parameter plants, was also obtained in [14]. These methods are mainly based on algebraic representations of input-output plants, and in particular on coprime factorizations (see [34,18,29] and [20] for time-delay systems). In [35], existence of a lumped approx-

imation in the graph topology is studied, and gives a clear interpretation of purely atomic parts in coprime factorizations that cannot be closed to lumped distributions, in the BIBO-stability framework. Instead of relaxing graph topology, we propose in this paper to generalize the approximation class of lumped systems by time-delay systems. While this class is still of infinite dimension and can exactly represent some partial differential equations [30], state-space realization and advanced tools for analysis and control reach nowadays maturity, and can therefore be of benefit to the study of distributed parameter systems. The main contribution of this paper is to show that, from a quantitative point of view, such a time-delay approximation always exists if a coprime factorization in the Wiener algebra of bounded input bounded output (BIBO) plants exists. This condition appears to be of practical relevance in constructive feedback perspective [32].

The paper is organized as follows. In Section 2, we briefly recall definitions and introduce some notations. Approximation by time-delay systems is developed in Section 3. In Section 4, we discuss on the state-space realization of the approximation class, and propose a numerical method with explicit construction. Two examples are illustrated in Section 5.

2 Preliminaries

In this section, some basic background and notations, that will be used throughout the paper, are introduced.

[★] This paper was not presented at any IFAC meeting. Corresponding author M. Di Loreto.

Email addresses: `michael.di-loreto@insa-lyon.fr` (Michaël Di Loreto), `serine.damak@insa-lyon.fr` (Sérine Damak), `damien.eberard@insa-lyon.fr` (Damien Eberard), `xavier.brun@insa-lyon.fr` (Xavier Brun).

2.1 Input-Output representation

A causal input-output convolution system is a dynamical system described by an equation of the form

$$y(t) = (Pu)(t) \doteq \int_0^t P(\tau)u(t-\tau) d\tau \quad (1)$$

where $y(\cdot)$, $u(\cdot)$ and $P(\cdot)$ are said to be the output, input and kernel of the plant, respectively. For our purpose, we consider the Wiener algebra of BIBO-stable systems [3], and we denote it by $\mathcal{A}$. We say that $P \in \mathcal{A}$ if $P = P_{\text{na}} + P_{\text{pa}}$ for $t \geq 0$ and 0 elsewhere, where $P_{\text{na}}(\cdot) \in L_1(0, \infty)$ (non atomic part), that is P_{na} is a real-valued function such that $\|P_{\text{na}}\|_{L_1} = \int_0^\infty |P_{\text{na}}(t)| dt$ is finite. The real-valued distribution P_{pa} stands for the purely atomic part

$$P_{\text{pa}}(t) = \sum_{n=0}^{\infty} P_n \delta(t - r_n) \doteq \sum_{n=0}^{\infty} P_n \delta_{r_n}(t), \quad (2)$$

with elements $\{P_n\}_{n \in \mathbb{N}}$ in $\mathbb{R}$, ordered delays $0 = r_0 < r_1 < \dots$, $\delta(t - r_n) = \delta_{r_n}(t)$ denoting the Dirac delta distribution centered in r_n , and $\sum_{n \geq 0} |P_n| < \infty$. The set $\mathcal{A}$ is a commutative convolution Banach algebra for the norm defined by

$$\|P\|_{\mathcal{A}} = \|P_{\text{na}}\|_{L_1} + \sum_{n=0}^{\infty} |P_n|, \quad (3)$$

with unit element the Dirac delta distribution δ . Denoting $\hat{P}$ the Laplace transform of P , $\hat{\mathcal{A}}$ is the set of Laplace transforms of elements in $\mathcal{A}$. The set $\mathcal{A}^{p \times m}$ stands for the set of $p \times m$ matrices P with entries in $\mathcal{A}$, and the matrix norm $\|P\|_{\mathcal{A}} = \max_{i=1, \dots, p} \sum_{j=1}^m \|P_{ij}\|_{\mathcal{A}}$, where P_{ij} denotes the (i, j) entry of P . Two matrices $N \in \mathcal{A}^{p \times m}$ and $D \in \mathcal{A}^{m \times m}$ are said to be right-coprime if there exist $X \in \mathcal{A}^{m \times p}$ and $Y \in \mathcal{A}^{m \times m}$ such that

$$XN + YD = I_m \delta, \quad (4)$$

where I_m stands for the $m \times m$ identity matrix. A pair (N, D) is a right-coprime factorization (r.c.f.) in $\mathcal{A}$ of a given plant P if D is non singular, $P = ND^{-1}$, and N, D are right-coprime over $\mathcal{A}$. Analogously, $(\tilde{D}, \tilde{N})$ is a left-coprime factorization (l.c.f.) in $\mathcal{A}$ of P if $\tilde{D}$ is non singular, $P = \tilde{D}^{-1}\tilde{N}$, and $\tilde{D} \in \mathcal{A}^{p \times p}$, $\tilde{N} \in \mathcal{A}^{p \times m}$ are left coprime over $\mathcal{A}$, that is there exist $\tilde{X} \in \mathcal{A}^{m \times p}$ and $\tilde{Y} \in \mathcal{A}^{p \times p}$ such that $\tilde{N}\tilde{X} + \tilde{D}\tilde{Y} = I_p \delta$.

2.2 Properness, BIBO-stability and stabilization

Elements P in $\mathcal{A}$ are causal and proper, in the sense that $\sup_{\text{Re}(s) \geq 0, |s| \geq r} |\hat{P}(s)|$ is bounded for some $r > 0$ [5, 4]. Elements P_{na} in the ideal $L_1(0, \infty)$ of $\mathcal{A}$ are strictly

proper, that is $\lim_{r \rightarrow \infty} \sup_{\text{Re}(s) \geq 0, |s| \geq r} |\hat{P}_{\text{na}}(s)|$ is zero [5, Property A.6.2 pp. 636]. A matrix of transfer functions $\hat{P}$ is said to be proper (strictly proper) if its entries are proper (strictly proper). Let P be a $p \times m$ causal plant, and assume that P admits a r.c.f. (N, D) , with $N \in \mathcal{A}^{p \times m}$ and $D \in \mathcal{A}^{m \times m}$. Using the Bézout identity (4), it is readily verified that P is proper if and only if D^{-1} is causal and proper. For $D = D_{\text{pa}} + D_{\text{na}}$, with $D_{\text{pa}} = \sum_{i \geq 0} D_i \delta_{r_i}$, this in turn implies that D_0 is invertible in $\mathbb{R}^{m \times m}$.

A causal convolution system $y = Pu$ is said to be BIBO stable if $P \in \mathcal{A}^{p \times m}$ [34], in the sense that any bounded input yields a bounded output. In control perspective, let C be a controller with a l.c.f. $(\tilde{D}_c, \tilde{N}_c)$ in $\mathcal{A}^{m \times m} \times \mathcal{A}^{m \times p}$, interconnected with the plant P as represented in Figure 1. The feedback system in Figure 1 satisfies $\mathbf{y} = W_{P,C} \mathbf{u}$, where

$$W_{P,C} = \begin{bmatrix} I_p \delta - N \Lambda^{-1} \tilde{N}_c & -N \Lambda^{-1} \tilde{D}_c \\ D \Lambda^{-1} \tilde{N}_c & D \Lambda^{-1} \tilde{D}_c \end{bmatrix}, \quad (5)$$

with $\mathbf{y} = \begin{bmatrix} y_1^T & y_2^T \end{bmatrix}^T$, $\mathbf{u} = \begin{bmatrix} u_1^T & u_2^T \end{bmatrix}^T$ and

$$\Lambda = \tilde{N}_c N + \tilde{D}_c D. \quad (6)$$

The pair (P, C) is said to be stable, or C stabilizes P , if $W_{P,C} \in \mathcal{A}^{(p+m) \times (p+m)}$. It is well known that (P, C) is stable if and only if Λ in (6) is a unit in $\mathcal{A}^{m \times m}$, that is Λ^{-1} exists and lies in $\mathcal{A}^{m \times m}$ [34, 29].

Fig. 1. Interconnection (P, C) by output feedback.

As an illustration, an acoustic wave in a duct with Dirichlet boundary conditions and a boundary constant impedance writes [4, Section 3.3 pp. 1106]

$$\hat{P}(s) = \frac{1 + \eta e^{-rs}}{1 - \eta e^{-rs}} \quad (7)$$

where η is the reflection coefficient such that $|\eta| < 1$. This proper and stable plant admits the coprime factorization in $\mathcal{A}$ described by

$$\hat{N}(s) = 1 + \eta e^{-rs}, \text{ and } \hat{D}(s) = 1 - \eta e^{-rs}, \quad (8)$$

where $D = \delta - \eta \delta_r$ is a unit in $\mathcal{A}$. This coprime factorization satisfies (4) with

$$\hat{X}(s) = -\hat{Q}(s)\hat{D}(s), \hat{Y}(s) = \hat{D}(s)^{-1} + \hat{Q}(s)\hat{N}(s),$$

for any $Q \in \mathcal{A}$. Another example issued from [1] and the theory of transmission lines is

$$\hat{P}(s) = \frac{e^{-\sqrt{s}}}{s-1} \quad (9)$$

with a simple pole at $s = 1$. A coprime factorization in $\mathcal{A}$ is $\hat{N}(s) = \frac{e^{-\sqrt{s}}}{s+1}$ and $\hat{D}(s) = \frac{s-1}{s+1}$, which satisfies (4) for

$$\hat{X}(s) = -\frac{4e}{s+1} \text{ and } \hat{Y}(s) = \frac{(s+1)^2 - 4ee^{-\sqrt{s}}}{(s+1)(s-1)},$$

where it is noted that $\hat{Y}(s) \in \mathcal{A}$ has a removable singularity at $s = 1$.

2.3 Graph topology and approximation

Graph topology gives a suitable framework for approximation in feedback perspective and robustness issues. We refer to [33,34,37] for details on this topology. For a causal plant P with a r.c.f. (N, D) , $N \in \mathcal{A}^{p \times m}$, $D \in \mathcal{A}^{m \times m}$, a neighbourhood of P in the graph topology can be characterized by convergence of coprime factorizations [34, ch. 7 p. 238]. For this, we consider the following definition.

Definition 1 For a subalgebra $\mathcal{S}$ in $\mathcal{A}$, we say that the sequence $\{P_\nu\}_{\nu \in \mathbb{N}}$, with $P_\nu = N_\nu D_\nu^{-1}$, $N_\nu \in \mathcal{S}^{p \times m}$ and $D_\nu \in \mathcal{S}^{m \times m}$, is an approximation of $P = ND^{-1}$ (in the graph topology) if for any $\epsilon > 0$, there exists ν_ϵ such that $P_{\nu_\epsilon} \in \mathcal{B}(P, \epsilon)$, where

$$\mathcal{B}(P, \epsilon) = \{P_\nu = N_\nu D_\nu^{-1}, \left\| \begin{bmatrix} N - N_\nu \\ D - D_\nu \end{bmatrix} \right\|_{\mathcal{A}} < \epsilon\}. \quad (10)$$

It is noted that, for the r.c.f. (N, D) in $\mathcal{A}$ of P , its approximation (N_ν, D_ν) is a r.c.f. in $\mathcal{S}$ of P_ν , for any sufficiently small ϵ [34, p. 235]. Approximation by lumped systems in graph topology was studied in [35], and comes down to define the approximation subset $\mathcal{S}$ in Definition 1 as the set of BIBO-stable lumped systems in the form

$$P(t) = P_0 \delta(t) + \sum_{i,j} P_{ij} t^j e^{-\lambda_i t}, \quad t \geq 0, \quad (11)$$

where P_0 and P_{ij} are complex numbers, $\text{Re}(\lambda_i) > 0$ for all i , and the sums are finite. A necessary and sufficient condition for the existence of a lumped approximation was established in the following result.

Theorem 2 [35] Let P be a plant with a r.c.f. (N, D) , $N \in \mathcal{A}^{p \times m}$, $D \in \mathcal{A}^{m \times m}$. Then P can be approximated by a lumped plant in the graph topology if and only if there exists a constant matrix $M \in \mathbb{R}^{p \times (m+p)}$ of rank p such that

$$M \begin{bmatrix} N_{\text{pa}} \\ D_{\text{pa}} \end{bmatrix} = 0.$$

For illustration, consider the plant P in (7) with the coprime factorization (8), where $N = N_{\text{pa}} = \delta + \eta \delta_r$ and $D = D_{\text{pa}} = \delta - \eta \delta_r$. It is trivial to see that Theorem 2 is not fulfilled, or equivalently that P cannot be approximated by a lumped plant in the graph topology.

A direct consequence of Theorem 2 is that any element in $L_1(0, \infty)$, which is strictly proper, can be approximated in the graph topology by a lumped plant. See also [15].

3 Approximation by delay systems

The limits that appear in lumped approximation motivate to consider a larger class of approximation, with the introduction of a time-delay operator.

3.1 Class of Approximation

Take the class of approximation as systems governed by continuous-time equations with time-delay in the form

$$\dot{\chi}(t) = \sum_{i=1}^s A_i \chi(t - r_i) + Ew(t) + Bu(t) \quad (12)$$

$$\dot{w}(t) = Hw(t) + G\chi(t) \quad (13)$$

$$y_\nu(t) = \sum_{i=0}^s C_i \chi(t - r_i) + Lw(t) \quad (14)$$

for $t \geq 0$ and ordered delays $0 = r_0 < r_1 < \dots < r_s$. The initial conditions are $\chi(t) = \varphi_\chi(t)$ for $t \in [-r_s, 0)$ (continuous and bounded) and $w(0) = w_0$. The equations (12)-(13) are (a particular case of) coupled differential-difference equations in standard form [11,12]. As a preliminary result which will be used in the general approximation procedure, let us start with the particular case of stable plants with only purely atomic part, which can be approximated in the graph topology by an input-delay system.

Lemma 3 Let $P \in \mathcal{A}^{p \times m}$ and assume that $P = P_{\text{pa}}$. Then P can be approximated in the graph topology by a coupled differential-difference system in the form (12)-(14).

PROOF. From assumption $P = P_{\text{pa}}$, the input-output plant $y = Pu$ is described by $P = \sum_{i \geq 0} P_i \delta_{r_i}$. Since

$\{P_i\}_{i \in \mathbb{N}}$ is convergent (see (2)-(3)), for any $\epsilon > 0$, there exists ς in $\mathbb{N}$ such that the truncation $\sum_{i=0}^{\varsigma} P_i \delta_{r_i}$ lies in $\mathcal{B}(P, \epsilon)$. Such an approximation admits a state-space realization in the form (12)–(14), with $\chi = u$, $w = 0$ and $C_i = P_i$, for $i = 0, \dots, \varsigma$. $\square$

3.2 Approximation by coupled differential-difference systems

From this preliminary result, let us consider the general case.

Theorem 4 *Let P be a causal and proper plant with a r.c.f. (N, D) , $N \in \mathcal{A}^{p \times m}$, $D \in \mathcal{A}^{m \times m}$. Then P can be approximated in the graph topology by a model governed by coupled differential-difference equations.*

PROOF. Let $y = Pu$, and introduce the partial state $\xi(\cdot)$ in $\mathbb{R}^m$ such that $u = D\xi$ and $y = N\xi$. This proof aims to construct a coprime factorization (N_ν, D_ν) for the approximation such that $P_\nu = N_\nu D_\nu^{-1}$ lies in $\mathcal{B}(P, \epsilon)$, for some fixed arbitrary $\epsilon > 0$. For this, denote $D = \sum_{i \geq 0} D_i \delta_{r_i} + D_{\text{na}}$. From Section 2.2, since P is causal and proper, D_0 is nonsingular, so that $u = D\xi$ can be put in the form

$$\begin{aligned} \hat{\xi}(s) = & - \sum_{i \geq 1} D_0^{-1} D_i e^{-sr_i} \hat{\xi}(s) - D_0^{-1} \hat{D}_{\text{na}}(s) \hat{\xi}(s) \\ & + D_0^{-1} \hat{u}(s). \end{aligned} \quad (15)$$

The term $D_0^{-1} \hat{D}_{\text{na}}$ is strictly proper (and BIBO-stable), and can therefore be approximated by a lumped system in the graph topology [35]. It follows that there exist $\kappa_D \in \mathbb{N}$ and real matrices $(E_{\kappa_D}, H_{\kappa_D}, G_{\kappa_D})$, respectively in $\mathbb{R}^{m \times \kappa_D}$, $\mathbb{R}^{\kappa_D \times \kappa_D}$ and $\mathbb{R}^{\kappa_D \times m}$, such that $E_{\kappa_D}(sI_{\kappa_D} - H_{\kappa_D})^{-1}G_{\kappa_D}$ realizes a lumped approximation of $D_0^{-1} \hat{D}_{\text{na}}$ in the graph topology. For the approximation of the purely atomic part $\sum_{i \geq 1} D_0^{-1} D_i \delta_{r_i}$ in (15), we use Lemma 3 with the truncation of the first ς_D terms, for some $\varsigma_D \in \mathbb{N}$. Hence, an approximation in the graph topology of $u = D\xi$ writes $u = D_\nu \chi$, for $\chi(\cdot) \in \mathbb{R}^m$, and is realized by the state-space equations

$$\begin{aligned} \chi(t) = & - \sum_{i=1}^{\varsigma_D} D_0^{-1} D_i \chi(t - r_i) - E_{\kappa_D} w_D(t) + D_0^{-1} u(t) \\ \dot{w}_D(t) = & H_{\kappa_D} w_D(t) + G_{\kappa_D} \chi(t). \end{aligned}$$

For the relationship $y = N\xi$, we have $N = N_{\text{pa}} + N_{\text{na}}$. Similarly, N_{na} is approximated by a lumped system realized by $(L_{\kappa_N}, H_{\kappa_N}, G_{\kappa_N})$, in respectively $\mathbb{R}^{p \times \kappa_N}$, $\mathbb{R}^{\kappa_N \times \kappa_N}$ and $\mathbb{R}^{\kappa_N \times m}$, for some $\kappa_N \in \mathbb{N}$. N_{pa} is truncated to its first ς_N terms, with $\varsigma_N \in \mathbb{N}$. The approxi-

mation of $y = N\xi$ is therefore $y_\nu = N_\nu \chi$, governed by

$$\begin{aligned} \dot{w}_N(t) = & H_{\kappa_N} w_N(t) + G_{\kappa_N} \chi(t) \\ y_\nu(t) = & \sum_{i=0}^{\varsigma_N} N_i \chi(t - r_i) + L_{\kappa_N} w_N(t). \end{aligned}$$

Let $w^T = [w_D^T \ w_N^T]$ and $\varsigma = \max(\varsigma_D, \varsigma_N)$. Combining the previous identities leads to the state-space equations in the form (12)–(14), where $A_i = -D_0^{-1} D_i$, $C_i = N_i$, $B = D_0^{-1}$, $E = [-E_{\kappa_D} \ 0]$, $L = [0 \ L_{\kappa_N}]$ and

$$H = \begin{bmatrix} H_{\kappa_D} & 0 \\ 0 & H_{\kappa_N} \end{bmatrix}, \quad G = \begin{bmatrix} G_{\kappa_D} \\ G_{\kappa_N} \end{bmatrix}. \quad (16)$$

By convention, the terms C_i and A_i are zero if they are not defined. $\square$

In the proposed approximation, the partial state $\chi(\cdot)$ lies in $\mathbb{R}^m$, while $w(\cdot) \in \mathbb{R}^{\kappa_D + \kappa_N}$ has a dependent dimension with respect to the desired accuracy of the approximation for the non atomic parts. Purely atomic parts lead to ς pointwise (*a priori* independent) delays in (12)–(14). The accuracy of the approximation P_ν is completely characterized by the parameters $(\kappa_N, \varsigma_N, \kappa_D, \varsigma_D)$, which define the order of the approximation.

4 Discussion and numerical method

4.1 Stabilization and input-output performances

Let P_ν be an approximation in the graph topology of P , realized, as explained in Section 3.2, by a time-delay system governed by the coupled differential-difference equations (12)–(14). Following Section 2.2, assume that C , which is causal and proper with a l.c.f. $(\tilde{D}_c, \tilde{N}_c)$, stabilizes P_ν , with a r.c.f. (N_ν, D_ν) . Such synthesis may be obtained by advanced tools in delay systems, see [20, 28, 16, 9, 6] and references therein. Denote

$$\Lambda_\nu = \tilde{N}_c N_\nu + \tilde{D}_c D_\nu \quad (17)$$

the unit matrix in $\mathcal{A}^{m \times m}$. For Λ defined in (6), we have

$$\Lambda = \Lambda_\nu \left(I_m \delta + \Lambda_\nu^{-1} \begin{bmatrix} \tilde{N}_c & \tilde{D}_c \end{bmatrix} \begin{bmatrix} N - N_\nu \\ D - D_\nu \end{bmatrix} \right). \quad (18)$$

It follows that (P, C) is stable if and only if Λ is a unit in $\mathcal{A}^{m \times m}$. Hence, a sufficient condition for stabilization is that

$$\left\| \begin{bmatrix} N - N_\nu \\ D - D_\nu \end{bmatrix} \right\|_{\mathcal{A}} < \frac{1}{\left\| \Lambda_\nu^{-1} \begin{bmatrix} \tilde{N}_c & \tilde{D}_c \end{bmatrix} \right\|_{\mathcal{A}}}, \quad (19)$$

which always admits a solution for $P_\nu \in \mathcal{B}(P, \epsilon)$ and a sufficiently small $\epsilon > 0$. In other words, if a coprime factorization (N, D) exists in $\mathcal{A}$, stabilization may be achieved using an approximation (N_ν, D_ν) as in Theorem 4 and a controller synthesized by time-delay tools. Remark also that, for input-output performance, the realized approximation leads to the input-output norm of the closed-loop plants $\|W_{P,C} - W_{P_\nu,C}\|_{\mathcal{A}}$ that can be arbitrarily reduced as far as the approximation is closed, where $W_{P,C}$ is defined in (5). The norm in $\mathcal{A}$ being an upper bound for L_2 -induced norm, this shows in particular that gain and phase approximations in frequency domain hold.

4.2 State-space realization

Few comments on the state-space realization (12)–(13) are in order. For notations convenience, we only consider the single delay case ($\varsigma = 1$ and $r = r_1$). While (12)–(13) appear in the standard form of coupled differential-difference equations (see [11] and references therein) for analysis, it may be preferred the canonical form where all terms in the right-hand side of (12) are delayed. For this, the realization of coupled differential-difference equations (12)–(13) is equivalent to the realization

$$\begin{aligned}\phi(t) &= A_1\phi(t-r) + A_1Ew(t-r) + A_1Bu(t-r) \\ \dot{w}(t) &= (H + GE)w(t) + G\phi(t) + GBu(t)\end{aligned}\quad (20)$$

using the combination of variables

$$\phi(t) = \chi(t) - Ew(t) - Bu(t),$$

for any $t \geq 0$. This form is the so-called Roesser canonical form for 2-D systems [7, 19]. It is well known that such a realization using a finite bank of operators is equivalent to neutral time-delay systems [19]. Note that the initial conditions for (20) are $\phi(t) = \varphi_\phi(t)$ for $t \in [-r, 0)$, $w(t) = \varphi_w(t)$ for $t \in [-r, 0]$, where $\varphi_\phi = \varphi_\chi - E\varphi_w$ (by convention $u(t) = 0$ for $t \in [-r, 0)$) and

$$\varphi_w(t) = e^{Ht}w_0 + \int_0^t e^{H(t-\tau)}G\varphi_\chi(\tau) d\tau. \quad (21)$$

The differential equation (13) can also be transformed into a difference equation with distributed delay. For this, the constant variation formula applied to (13) writes as

$$w(t) = e^{Hr}w(t-r) + \int_{t-r}^t e^{H(t-\tau)}G\chi(\tau) d\tau \quad (22)$$

for $t \geq 0$ and the initial condition $\varphi_w(\cdot)$ in (21). Combining (12) and (22) leads to the difference equation with distributed delay

$$x(t) = A_d x(t-r) + B_d u(t) + \int_{t-r}^t G_d(t-\tau)x(\tau) d\tau \quad (23)$$

for $t \geq 0$, where $x^T = [\chi^T \ w^T]$, $B_d^T = [B^T \ 0]$,

$$A_d = \begin{bmatrix} A_1 & E e^{Hr} \\ 0 & e^{Hr} \end{bmatrix}, G_d(t) = \begin{bmatrix} E e^{Ht} G & 0 \\ e^{Ht} G & 0 \end{bmatrix}.$$

In reformulating the coupled differential-difference equations (12)–(13) in difference equations with distributed delay (23), additional dynamics appear. Indeed, the characteristic polynomial associated to the initial formulation (12)–(13) is (in the single delay case)

$$\pi_c(\lambda) = \det(\lambda I_m - H - G(I_m - A_1 e^{-\lambda r})^{-1} E), \quad (24)$$

while for the difference formulation (23), the characteristic equation writes

$$\pi_d(\lambda) = \pi_c(\lambda)\pi_{dd}(\lambda), \quad (25)$$

with

$$\pi_{dd}(\lambda) = \det((I_m - e^{-(\lambda I_m - H)r})(\lambda I_m - H)^{-1}). \quad (26)$$

$\pi_{dd}(\lambda)$ is actually a strictly proper pseudo-polynomial in λ [20], and more precisely it is an entire function and has no pole. Additional zeros of $\pi_{dd}(\lambda)$ with respect to (24) are obtained in (26), and lie in the set

$$\lambda \in \{\sigma(H) + i \frac{2\pi k}{r}, \ k = \pm 1, \pm 2, \dots\}, \quad (27)$$

where $\lambda \notin \sigma(H)$, $\sigma(H)$ denoting the eigenvalues of H . Additional dynamics are, in the complex plane, along vertical chains with real parts located at $\text{Re}(\sigma(H))$. It follows that, since H is Hurwitz (see (16) and (31)), stability of the realizations (12)–(13) and (23) are equivalent.

4.3 Numerical approximation

The numerical computation of the time-delay system that approximates P in the graph topology requires, from a coprime factorization (N, D) , to truncate the atomic parts (N_{pa}, D_{pa}) , and to realize a $L_1(0, \infty)$ approximation of the non atomic parts (N_{na}, D_{na}) . This last part may be realized by any convergent method in $L_1(0, \infty)$, as for instance in [10, 13]. For direct computations in the Laplace domain, Laguerre polynomials are applied. See [31] and [21] for Laguerre approximation techniques of distributed parameter systems. Let us denote the Laguerre polynomials

$$p_\kappa(t) = \frac{e^t}{\kappa!} \frac{d^\kappa}{dt^\kappa} (e^{-t} t^\kappa) = \sum_{k=0}^{\kappa} \binom{\kappa}{k} \frac{(-t)^k}{k!}, \quad \kappa \in \mathbb{N}.$$

The elements $g_\kappa(t) = p_\kappa(t)e^{-t/2}$, for $\kappa \geq 0$, form an orthonormal basis of $L_2(0, \infty)$, and any function $P \in$

$L_2(0, \infty)$ can be expanded as $P(t) = \sum_{\kappa=0}^{\infty} c_{\kappa}(P)g_{\kappa}(t)$, where $c_{\kappa}(P) = \langle P, g_{\kappa} \rangle = \int_0^{\infty} P(t)g_{\kappa}(t)dt$ are the Laguerre coefficients of P relative to g_{κ} [31]. Assume that there exists $\alpha_0 > 0$ such that $e^{\alpha_0 t}P(t) \in L_2(0, \infty)$. For any $\alpha \in (0, \alpha_0)$, it has been shown in [17] that the function

$$P_{\nu, \alpha}(t) = \sum_{\kappa=0}^{\nu} c_{\kappa, \alpha}(P)g_{\kappa}(t)e^{-\alpha t}, \quad (28)$$

with $c_{\kappa, \alpha}(P) = \langle e^{\alpha t}P(t), g_{\kappa}(t) \rangle$, lies in $L_1(0, \infty) \cap L_2(0, \infty)$, and converges to P in $L_1(0, \infty)$, that is

$$\lim_{\nu \rightarrow \infty} \|P - P_{\nu, \alpha}\|_{L_1} = 0. \quad (29)$$

The computation of the coefficients $c_{\kappa, \alpha}(P)$ is made directly in the Laplace domain, by the formula

$$c_{\kappa, \alpha}(P) = \sum_{k=0}^{\kappa} \binom{\kappa}{k} \frac{1}{k!} \hat{P}^{(k)}\left(\frac{1}{2} - \alpha\right), \quad (30)$$

where $\hat{P}^{(k)}$ stands for the k th derivative of $\hat{P}$, and the approximation (28) leads to (see [31, p. 379])

$$\hat{P}_{\nu, \alpha}(s) = \sum_{\kappa=0}^{\nu} c_{\kappa, \alpha}(P) \frac{(s + \alpha - \frac{1}{2})^{\kappa}}{(s + \alpha + \frac{1}{2})^{\kappa+1}}. \quad (31)$$

Particularizing this method for N_{na} and $D_0^{-1}D_{\text{na}}$ and using a state-space realization for (31) leads to a constructive approximation of the quadruple (H, E, L, G) in (16) and (12)-(14) for the non atomic parts, while N_{pa} and $D_0^{-1}D_{\text{pa}}$ are truncated, as proposed in Lemma 3.

5 Illustrations

5.1 Coupled heat-transport equation

Consider the coupled partial differential equations with boundary conditions

$$\xi_t(z, t) = \vartheta^2 \xi_{zz}(z, t), \quad z \in (0, \ell), \quad t \geq 0, \quad (32)$$

$$\xi(0, t) = 0, \quad \xi(\ell, t) = u(t) - y(t), \quad (33)$$

for $\vartheta > 0$, zero initial conditions and the transport equation

$$w_t(z, t) + w_z(z, t) = 0, \quad z \in (0, \ell), \quad t \geq 0, \quad (34)$$

with the boundary condition $w(0, t) = \frac{1}{2}y(t)$. The output signal is defined by $y(t) = \xi(z_0, t) + w(z_0, t)$, for a fixed $z_0 \in (0, \ell)$. The input-output transfer function for (32)-(34) is $\hat{y}(s) = \hat{P}(s)\hat{u}(s)$, where

$$\hat{P}(s) = \frac{\frac{\sinh(\frac{z_0\sqrt{s}}{\vartheta})}{\sinh(\frac{\ell\sqrt{s}}{\vartheta})}}{1 - \frac{1}{2}e^{-z_0s} + \frac{\sinh(\frac{z_0\sqrt{s}}{\vartheta})}{\sinh(\frac{\ell\sqrt{s}}{\vartheta})}}. \quad (35)$$

Fig. 2. Approximation error $|\hat{P}(j\omega) - \hat{P}_1(j\omega)|$ frequency diagram in (35)-(37) for the coupled heat-transport system.

Define $\hat{N}(s) = \frac{\sinh(\frac{z_0\sqrt{s}}{\vartheta})}{\sinh(\frac{\ell\sqrt{s}}{\vartheta})}$, $\hat{D}(s) = 1 - \frac{1}{2}e^{-z_0s} + \hat{N}(s)$.

The poles of $\hat{N}(s)$ are $-(\frac{k\pi\vartheta}{\ell})^2$, for $k = 1, 2, \dots$. This implies that $N(\cdot) \in \mathcal{A}$ and is strictly proper [4], and also that $D(\cdot) \in \mathcal{A}$. Furthermore, (N, D) is a coprime factorization of $\hat{P}(s)$, since $\hat{X}(s)\hat{N}(s) + \hat{Y}(s)\hat{D}(s) = 1$, with $\hat{X}(s) = -\hat{Y}(s) = -\frac{1}{1 - \frac{1}{2}e^{-z_0s}}$ elements in $\mathcal{A}$. The Laguerre approximation in $L_1(0, \infty)$ is realized for $N = N_{\text{na}}$ and $D_{\text{na}} = N$, since assumptions before (28) hold and α_0 can be taken in $(0, \frac{\pi^2\vartheta^2}{\ell^2})$. Simulations are obtained in Figures 2-3, for $\ell = 1$, $z_0 = \ell/2$, $\vartheta = 1$ and $\alpha = \frac{\pi^2\vartheta^2}{\ell^2} - \frac{1}{2}$. The approximation of $\hat{N}(s)$ with $\nu = 1$ in (28), and then of $\hat{D}_{\text{na}}(s)$, is realized by $\hat{N}_1(s) = E(sI_2 - H)^{-1}G$, where

$$H = \begin{bmatrix} -19.74 & -97.41 \\ 1 & 0 \end{bmatrix}, \quad G = \begin{bmatrix} 1 \\ 0 \end{bmatrix}, \quad E = \begin{bmatrix} 5.97 & 59.1 \end{bmatrix}.$$

The state-space realization of $\hat{P}_1(s)$ is

$$\chi(t) = \frac{1}{2}\chi(t - z_0) - Ew(t) + Bu(t) \quad (36)$$

$$\dot{w}(t) = Hw(t) + G\chi(t) \quad (37)$$

with $B = 0.912$ and the output of the approximation plant satisfies $y_1(t) = Ew(t)$. The frequency diagram of the error $|\hat{P}(j\omega) - \hat{P}_1(j\omega)|$ between the exact plant (35) and $\hat{P}_1(s)$ is reported in Figure 2. This gives an illustration of the approximated magnitude in the frequency domain (see below (19) in Section 4.1), related to the convergence of coprime factors in the $\mathcal{A}$ -norm, where $P_1 \in \mathcal{B}(P, 0.05)$. While the approximation is of first order $\nu = 1$ (corresponding to the Laguerre polynomial degree), its realization is obtained by a coupled scalar one-delay difference equation with a second order $(\nu + 1)$ differential equation only. Using [35, Th. 4.1], $\hat{P}(s)$ can

actually be approximated in the graph topology by a lumped system. However, lumped approximation may involve large-scale realization for a similar level of performance. This can be seen in Figure 3 where the unit step response for (36)-(37) reproduces with fidelity the transport-heat phenomenon considered in (32)-(34).

Fig. 3. Unit step response $y_1(t)$ of $\hat{P}_1(s)$ in (36)-(37) for the coupled heat-transport system.

5.2 Damped wave equation

As a second illustration, consider the damped wave equation

$$\xi_{zz}(z, t) = \frac{1}{c^2} \xi_{tt}(z, t) + \gamma \xi_t(z, t) + \mu \xi(z, t), \quad (38)$$

for $z \in (0, \ell)$, $t \geq 0$, with positive reals c , γ and μ , the boundary conditions

$$\xi(0, t) = 0, \quad \xi(\ell, t) = u(t), \quad (39)$$

and zero initial condition. Let

$$\varpi(s) = s^2 + c^2 \gamma s + c^2 \mu = (s + \frac{c^2 \gamma}{2})^2 + \eta, \quad (40)$$

with $\eta = c^2 \mu - \frac{c^4 \gamma^2}{4}$. From (38)-(39), the transfer function $\hat{\xi}(z, s) = \hat{P}(s) \hat{u}(s)$ is, for any $z \in (0, \ell)$,

$$\hat{P}(s) = \frac{\sinh(\frac{z}{c} \sqrt{\varpi(s)})}{\sinh(\frac{\ell}{c} \sqrt{\varpi(s)})}. \quad (41)$$

The poles of $\hat{P}(s)$ are, for $k = 1, 2, \dots$,

$$s_k = \begin{cases} -\frac{c^2 \gamma}{2} \pm i \sqrt{\eta + (\frac{k \pi c}{\ell})^2}, & -\frac{\eta \ell^2}{\pi^2 c^2} \leq k^2 \\ -\frac{c^2 \gamma}{2} \pm \sqrt{-\eta - (\frac{k \pi c}{\ell})^2}, & k^2 \leq -\frac{\eta \ell^2}{\pi^2 c^2} \end{cases}, \quad (42)$$

and satisfy $\text{Re}(s_k) \leq \max(-\frac{\mu}{\gamma}, -\frac{c^2 \gamma}{2})$. With the Bessel function

$$J_1(t) = \frac{1}{\pi} \int_0^\pi \cos(\tau - t \sin \tau) d\tau, \quad (43)$$

we remark that the following decomposition holds [36, p. 164]

$$e^{-\frac{\beta(z)}{c} \sqrt{\varpi(s)}} = e^{-\frac{c \gamma \beta(z)}{2}} e^{-\frac{\beta(z)}{c} s} - \hat{\psi}_{\beta(z)}(s), \quad (44)$$

where $\beta(z) = \ell + z$, $\varrho(t, \beta(z)) = \sqrt{t^2 - (\frac{\beta(z)}{c})^2}$,

$$\psi_{\beta(z)}(t) = \frac{\frac{\beta(z) \sqrt{\eta}}{c} e^{-\frac{c^2 \gamma}{2} t}}{\varrho(t, \beta(z))} J_1(\sqrt{\eta} \varrho(t, \beta(z))) h(t - \frac{\beta(z)}{c})$$

and $h(\cdot)$ stands for the Heaviside function. The function $\psi_{\beta(z)}(\cdot)$ lies in $L_1(0, \infty)$, so that, using (42), a coprime factorization in $\mathcal{A}$ for $\hat{P}(s)$ in (41) is

$$\hat{N}(s) = e^{-\frac{\ell-z}{c} \sqrt{\varpi(s)}} - e^{-\frac{\ell+z}{c} \sqrt{\varpi(s)}}, \quad (45)$$

$$\hat{D}(s) = 1 - e^{-\frac{2\ell}{c} \sqrt{\varpi(s)}}, \quad (46)$$

or equivalently

$$N(t) = e^{-\frac{\gamma c \beta(-z)}{2}} \delta(t - \frac{\beta(-z)}{c}) - e^{-\frac{\gamma c \beta(z)}{2}} \delta(t - \frac{\beta(z)}{c}) + \psi_{\beta(z)}(t) - \psi_{\beta(-z)}(t),$$

$$D(t) = \delta(t) - e^{-\frac{\gamma c \beta(\ell)}{2}} \delta(t - \frac{\beta(\ell)}{c}) + \psi_{\beta(\ell)}(t).$$

The non atomic parts of (45)-(46)

$$N_{\text{na}}(t) = \psi_{\beta(z)}(t) - \psi_{\beta(-z)}(t) \quad (47)$$

$$D_{\text{na}}(t) = \psi_{\beta(\ell)}(t) \quad (48)$$

are approximated in $L_1(0, \infty)$ by lumped plants, as proposed in Section 4.3, while purely atomic parts

$$N_{\text{pa}}(t) = e^{-\frac{\gamma c \beta(-z)}{2}} \delta(t - \frac{\beta(-z)}{c}) - e^{-\frac{\gamma c \beta(z)}{2}} \delta(t - \frac{\beta(z)}{c})$$

$$D_{\text{pa}}(t) = \delta(t) - e^{-\frac{\gamma c \beta(\ell)}{2}} \delta(t - \frac{\beta(\ell)}{c})$$

are conserved in the approximation. Simulations are carried out for $c = 1$, $\gamma = 1$, $\mu = 0.5$, $\ell = 1$ and $z = 0.3$, and the approximation technique proposed in Section 4.3 applies with $\alpha = \frac{c^2 \gamma}{2}$. Two approximations $P_\nu(t)$ of order $\nu = 1$ and $\nu = 8$ are reported in Figure 4, where the frequency diagram of the approximation error $|\hat{P}(j\omega) - \hat{P}_\nu(j\omega)|$ is reported. Approximations satisfy $P_1 \in \mathcal{B}(P, 0.14)$ and $P_8 \in \mathcal{B}(P, 0.07)$. In the first order

Fig. 4. Approximation error $|\hat{P}(j\omega) - \hat{P}_\nu(j\omega)|$ diagram in (41) and (47)-(48), with $\nu = 1$ (cont. line, blue) and $\nu = 8$ (dot line, red), for the wave equation (38)-(39).

case $\nu = 1$, the approximation P_1 is realized by

$$\begin{aligned}\chi(t) &= e^{-\frac{\gamma c \beta(\ell)}{2}} \chi(t - \frac{\beta(\ell)}{c}) - Ew(t) + u(t) \\ \dot{w}(t) &= Hw(t) + G\chi(t) \\ y_1(t) &= e^{-\frac{\gamma c \beta(-z)}{2}} \chi(t - \frac{\beta(-z)}{c}) - e^{-\frac{\gamma c \beta(z)}{2}} \chi(t - \frac{\beta(z)}{c}) \\ &\quad + Lw(t),\end{aligned}$$

where $L = \begin{bmatrix} -0.06 & 0.03 \end{bmatrix}$, $E = \begin{bmatrix} -0.14 & 0.12 \end{bmatrix}$ and

$$H = \begin{bmatrix} -2 & -1 \\ 1 & 0 \end{bmatrix}, G = \begin{bmatrix} 1 \\ 0 \end{bmatrix}.$$

Again, it is remarkable to verify that the first order approximation (corresponding to a second order differential equation coupled with a difference equation with one delay) can approximate the exact plant for all frequencies, which guarantees its pertinence in control perspectives.

6 Conclusion

In this paper, we define an approximation in the graph topology using norm convergence of a coprime factorization in the Wiener algebra. Such an approximation is governed by coupled continuous-time differential-difference equations. A constructive state-space realization is established, and a numerical method based on Laguerre polynomials is proposed and illustrated. Properties of this approximation appear to be of practical interest for control and simulation. While the content of this paper is not related to advances in quantitative aspects in topology, its interest is mainly in the existence result of the time-delay approximation and its perspective seen as a trade-off for analysis and synthesis

between distributed parameter systems and time-delay systems.

Acknowledgements

This work was supported by ANR project AIDS from the French National Research Agency, under grant ANR-11-JS03-0004.

References

- [1] C. Bonnet and J. R. Partington, Coprime factorizations and stability of fractional differential systems, *Systems & Control Letters*, vol. 41, 2000, pp. 167-174.
- [2] C. Bonnet and J. R. Partington, Bézout factors and L^1 -optimal controllers for delay systems using a two-parameter compensator scheme, *IEEE Trans. on Autom. Contr.*, vol. 44(8), 1999, pp. 1512-1521.
- [3] F. M. Callier and C. A. Desoer, An algebra of transfer functions for distributed linear time-invariant systems, *IEEE Trans. on Circuits Syst.*, vol. 25, 1978, pp. 651-662.
- [4] R. Curtain and K. Morris, Transfer functions of distributed parameter systems: A tutorial, *Automatica*, vol. 45, 2009, pp. 1101-1116.
- [5] R. F. Curtain and H. J. Zwart, *An introduction to infinite-dimensional linear systems theory*, Springer-Verlag, New York, 1995.
- [6] S. Damak and M. Di Loreto and S. Mondié, Stability of linear continuous-time difference equations with distributed delay: Constructive exponential estimates, *Int. J. Robust Nonlinear Contr.*, DOI: 10.1002/rnc.3249, p. 15, 2014.
- [7] R. Eising, Realization and stabilization of 2-D systems, *IEEE Trans. on Autom. Contr.*, vol. 23(5), 1978, pp. 793-799.
- [8] C. Foias and H. Özbay and A. Tannenbaum, *Robust control of infinite dimensional systems : Frequency domain methods*, LNCIS No. 209, Springer-Verlag, London, 1996.
- [9] E. Fridman, *Introduction to time-delay systems*, Birkhäuser, Basel, 2014.
- [10] K. Glover and R. F. Curtain and J. R. Partington, Realisation and approximation of linear infinite-dimensional systems with error bounds, *SIAM J. Control Opt.*, vol. 26(4), 1988, pp. 863-898.
- [11] K. Gu, Stability problem of systems with multiple delay channels, *Automatica*, vol. 46, 2010, pp. 743-751.
- [12] K. Gu, A review of some subtleties of practical relevance for time-delay systems of neutral type, *ISRN Applied Mathematics*, 2012, pp. 46.
- [13] G. Gu and P. P. Khargonekar and E. B. Lee, Approximation of infinite-dimensional systems, *IEEE Trans. on Autom. Contr.*, vol. 34(6), 1989, pp. 610-618.
- [14] E. W. Kamen and P. P. Khargonekar and A. Tannenbaum, Stabilization of time-delay systems using finite-dimensional compensators, *IEEE Trans. on Autom. Contr.*, vol. 30(1), 1985, pp. 75-78.
- [15] D. W. Kammler, Approximation with sums of exponentials in $L_p[0, \infty]$, *J. Approx. Theory*, vol. 16, 1976, pp. 384-408.
- [16] V. Kharitonov, *Time-delay systems, Lyapunov functionals and matrices*, Birkhäuser, Basel, 2013.

- [17] X. Li, L^1 Approximation of a certain class of infinite dimensional systems in time-domain, *IEEE Trans. on Circuits and Systems*, vol. 43(5), 1996, pp. 397-399.
- [18] H. L. Logemann, Stabilization and regulation of infinite-dimensional systems using coprime factorizations. In R.F. Curtain, A. Bensoussan & J. L. Lions (Eds.), *LNCIS: Vol.185. Analysis and optimization of systems: State and frequency domain approaches for infinite dimensional systems*, Berlin: Springer-Verlag, 1993, pp. 102-139.
- [19] J. J. Loiseau and D. Brethé, The use of 2-D systems theory for the control of time-delay systems, *JESA*, vol. 45(6), 1997, pp. 1043-1058.
- [20] J. J. Loiseau, Algebraic tools for the control and stabilization of time-delay systems, *Annual Reviews in Control*, vol. 24, 2000, pp. 135-149.
- [21] P. M. Mäkilä, Laguerre series approximation of infinite dimensional systems, *Automatica*, vol. 26(6), 1990, pp. 985-995.
- [22] P. M. Mäkilä and J. R. Partington, Robust stabilization-BIBO Stability, Distance Notions and Robustness Optimization, *Automatica*, vol. 23(3), 1993, pp. 681-693.
- [23] K. A. Morris, Design of finite-dimensional controllers for infinite-dimensional systems by approximation, *J. of Mathematical Systems, Estimation and Control*, vol. 4(2), 1994, pp. 1-30.
- [24] K. A. Morris, H_∞ output feedback control of infinite-dimensional systems via approximation, *Systems & Control Letters*, vol. 44(3), 2001, pp. 211-217.
- [25] T. Myint-U and L. Debnath, *Linear partial differential equations for Scientists and Engineers*, 4th Ed., Birkhäuser, Boston, 2007.
- [26] J. R. Partington and K. Glover, Robust stabilization of delay systems by approximation of coprime factors, *Systems & Control Letters*, vol. 14, 1990, pp. 325-331.
- [27] J. R. Partington, Approximation of unstable infinite-dimensional systems using coprime factors, *Systems & Control Letters*, vol. 16, 1991, pp. 89-96.
- [28] P. Pepe and E. I. Verriest, On the stability of coupled delay differential and continuous time difference equations, *IEEE Trans. on Autom. Contr.*, vol. 48(8), 2003, pp. 1422-1427.
- [29] A. Quadrat, On a generalization of the Youla-Kučera parametrization. Part I : The fractional ideal approach to SISO systems, *Systems & Control Letters*, vol. 50, 2003, pp. 135-148.
- [30] V. Răsvan, Functional differential equations and one-dimensional distortionless propagation, *Tatra Mt. Publ.*, vol. 43, 2009, pp. 215-228.
- [31] G. Szegő, *Orthogonal polynomials*, 4th Ed., AMS Press, Providence, Rhode Island, 1975.
- [32] M. Vidyasagar and H. Schneider and B. A. Francis, Algebraic and topological aspects of feedback stabilization, *IEEE Trans. on Autom. Contr.*, vol. 27(4), 1982, pp. 880-894.
- [33] M. Vidyasagar, The graph metric for unstable plants and robustness estimates for feedback stability, *IEEE Trans. on Autom. Contr.*, vol. 29, 1984, pp. 403-418.
- [34] M. Vidyasagar, *Control System Synthesis. A Factorization Approach*, MIT Press, Cambridge, Massachusetts, 1985.
- [35] M. Vidyasagar and B. D. O. Anderson, Approximation and stabilization of distributed systems by lumped systems, *Systems & Control Letters*, vol. 12, 1989, pp. 95-101.
- [36] K. Yosida, *Operational calculus. A theory of hyperfunctions*, Applied Mathematical Sciences Vol. 55, Springer-Verlag, New York, 1984.
- [37] S. Q. Zhu, A graph metric for a class of MIMO linear distributed systems. In A. Bensoussan & J. L. Lions (Eds.), *LNCIS: Vol.111. Analysis and optimization of systems*, Berlin: Springer-Verlag, 1988, pp. 1091-1102.
- [38] H. J. Zwart, Transfer functions for infinite-dimensional systems, *Systems & Control Letters*, vol. 52, 2004, pp. 247-255.