A concurrent 915 MHz / 2440 MHz RF Energy Harvester

L. Fadel¹, L. Oyhenart¹, R. Bergès¹, V. Vigneras¹, T. Taris¹

¹ Laboratoire IMS, UMR - 5218, Université de Bordeaux, 33405 Talence Cedex, France.

This paper presents the development of two dual-band RF harvesters optimized to convert far-field RF energy to DC voltage at very low received power. The first one is based on a patch antenna and the second on a dipole antenna. They are both implemented on a standard FR4 substrate with commercially off-the-shelf (COTS) devices. The two RF harvesters provide a rectified voltage of 1V for a combined power respectively of -19.5 dBm at 915 MHz and -25 dBm at 2.44 GHz and of -20 dBm at 915 MHz and -15 dBm at 2.44 GHz. The remote powering of a clock consuming 1V/5μA is demonstrated, and the rectenna yields a power efficiency of 12 %.

Keywords: Antennas and Propagation for Wireless Systems, Applications and Standards (mobile, Wireless, networks), Circuit Design and Applications.

Corresponding author: email: ludivine.fadel@ims-bordeaux.fr; phone: +33 540 002 615

I. INTRODUCTION

Today's the society is evolving toward creating smart environments where a multitude of sensors and devices are interacting to deliver an abundance of useful information. Essential to the implementation of this Internet Of Things (IOT) is the design of energy efficient solutions aiming toward a low-carbon-emission, namely green, society. Within this context, the energy harvesting appears as an alternative to provide systems with self-sustained operation. Many electronic devices operate in conditions where it is costly, inconvenient, or impossible to replace the battery. Examples include sensors for health monitoring of patients [1],[2], aircraft or building structural monitoring [3],[4], sensors in natural, industrial or hazardous environments, etc. The scavenging of natural ambient energy requires some specific conditions such as: daylight for solar energy [5], breeze for wind energy or motion for kinetic energy [6] to name a few. As consequences the exploitation of natural source does not fit with many cases of applications. On the other hand the electromagnetic (EM) [7], or Radio-Frequency (RF), energy is a human made source that is not dependent of weather conditions nor the daytime. It is so very attractive for wireless powering of remote devices. Furthermore the ever growing of commercial and personal wireless installations opens up to a 24 hour a day available energy in the vicinity of any human activity areas. The schematic of a general Wireless RF Power Transmission (WPT) system is shown in Fig.1. We talk here about far-field RF energy transmission [8], which is different from near-field RF energy transmission [9]. This later including inductive, capacitive or resonant coupling is a close contact transmission and is not relevant for remote devices. In Fig. 1, the receiver antenna

collects the EM energy radiated by a RF source, and converts it into a RF signal. This RF signal is transferred to the rectifier by an impedance matching network, to be converted into DC power, which is further accumulated in a storage element. The main purpose in the deployment of WPT systems is the development of compact and efficient solutions. Most of the challenge concerns the implementation of harvesting modules, especially the antenna as its design defines the scavenging capability and the size of the RF harvester. At low frequency the transfer of energy is efficient, but the antenna footprint is large. To address the trade off between the efficiency of the WPT and the size of the modules, the frequency band located in the 433 MHz to 6 GHz frequency spectrums are preferred.

Fig. 1: Schematic of a Wireless RF Power Transmission (WPT) system

Over the last decade the research effort has focused on the development of WPT systems according two scenarios: the RF energy scavenging [10] and the RF energy transfer [11]. The two RF energy scavenging is an opportunistic collection of the RF ambient energy from the surrounding communication traffic. To improve the harvesting capability the scavenging RF harvesters are of wide-band type [12] and cover popular standards such as: DTV (470-610 MHz), GSM900, GSM1800, 3G (2.1GHz) and WiFi (2.4 GHz). Unfortunately these standards dedicated to convey wireless communications do not radiate a large RF power. As consequences the collected energy is weak, unpredictable and out of control. The RF energy scavenging remains a promising solution in the future as the increase of communication traffic could make it more reliable, and consistent with IOT applications. The second concept, namely RF energy transfer, assumes an identified source that is dedicated to perform the WPT. The amount of transmitted power is controlled by the source and the collected energy is larger than in scavenging approach. The licence-free Industry-Science-Medical (ISM) frequency bands located at 0.9, 2.4 and 5.8 GHz are usually exploited to support such a WPT scenario. Today the RF energy transfer in ISM Bands is not only promising, it becomes a reality as some pioneer companies propose some full kits: Powercast Corporation, AnSem and MicroChip to name a few. However there is still a lot of work to make the RF energy transfer an appropriate, low cost and easy-to-use solution for remote powering. One of the most critical point concerns the harvesting capability of the RF modules. So far the commercial kits referenced above only explore the 900 MHz ISM allocations to perform the WPT. This work proposes to demonstrate the interest of a concurrent harvesting at 915 MHz and 2.44 GHz. The design and implementation of a modified 4-stage doubler RF to DC converter, including a concurrent matching network, is first presented. The section III details the design of two types of multi-band antenna. The comparison between a single frequency and a multi-band WPT is exposed and the demonstration of the remote powering of a clock is reported as a case of application. To conclude a comparison of our results with the state of the art is exposed.

II. CONCURRENT RF TO DC CONVERTER

The Radio-Frequency IDentification (RFID) applications are the most popular systems exploiting the principle of RF energy transport. In passive RFID applications the reader transmits the RF power to the tag, and also sets up the communication. The RF to DC converter is designed to yield a maximum of power efficiency to the tag. Most of the time the reader and the tag are in line of sight and close to each other, these conditions improve the transmission of RF energy, the amount of power available at the tag antenna is large, typically between -15 dBm and -20 dBm. In RF energy harvesting the scenario is different. The distance between the RF source and the RF harvester ranges from 0.5 meter to 10 meters. The amount of collectable power is low, from -10 dBm to -25 dBm, and the remote powering is difficult. The RF harvesters are supposed to collect and to store the energy during a long period of time. Once the level of stored energy is large enough, it can be released to the application. For these reasons a rectifier dedicated to RF energy harvesting is first designed to yield a maximum of sensitive to increase its scavenging time and capability.

A) Rectifier Architecture

The rectifier architecture is based on voltage multipliers to provide an adequate output DC voltage. The architecture of the RF to DC converter, reported in Fig.2, includes a matching network based on a L-section, and a N-stage voltage multiplier based on Schottky diodes from Avago (HSMS285). The choice of the Schottky diode is very important in the design of the rectifier. A key parameter is its threshold voltage V_{TH} . When only low power levels are available in the environment, the amplitude of the incident signal may be close to or even below this voltage. Below this voltage value, the diode will no longer conduct and the losses become predominant. For COTS devices the two Schottky diodes performing the best conversion efficiency in a 2.4 GHz range are HSMS-2850 from Avago and SMS-7630 from Skyworks [13].

Fig. 2: Architecture of the RF to DC converter

Focusing on the sensitivity, the RF to DC converter is designed to maximize the rectified voltage for an input power close to -20 dBm. The optimum number of stage is fixed to four according [14]. The footprint of each voltage doubler imposes the micro-strip line network. The micro-strip lines namely “junction” is set to minimum length, the micro-strip lines “access” are used as an additional degree to tune the input-matching network. Indeed, the L section in combination with the micro-strip distributed network is equivalent to a T section (Fig.3). Many combinations of Z_1 , Z_2 , Z_3 can achieve input matching at 900 MHz or 2.4 GHz. Some of them are very close for each frequency, so we choose one that allows a return loss (< -10 dB at least) both at 900 MHz and 2.4 GHz.

Fig. 3: Topology of the input-matching network

The equivalent narrow band model of the matching network is proposed for each frequency (Fig.4). At 915 MHz, the voltage multiplier, including the rectification stages and the micro-strip line network, is modelled with a shunt capacitor (5pF) and a shunt resistor of 270 Ω (Fig.4a). The stub, (Fig.3) is equivalent to an inductor (Fig.4a), which compensates the shunt capacitor. The input micro-strip line, (Fig.3), is a quarter wave impedance transformer, (Fig.4a) it converts the 270 Ω into 50 Ω . At 2.44 GHz the micro-strip line network distributing the RF signal to the voltage doublers (Fig.3), becomes inductive (Fig.4b). The stub is equivalent to a shunt capacitor of 120fF, its effect is negligible. The impedance transformation is actually performed by the input micro-strip line, which is modelled by a shunt capacitor (0,6 pF) and a series inductor of 5.6 nH.

Fig. 4: Equivalent model of the input matching network at 915 MHz (a) at 2,44 GHz (b)

To study the impact of the power on the diode, and input matching, behaviour the return loss of the 4-stage rectifier has been measured and plotted (Fig.5) for various input power P_{rf} at 900MHz.

Fig. 5: Measured S_{11} of a 4-stage voltage multiplier with a L section at 900 MHz for various input power P_{rf}

As illustrated in the figure 5, the input return loss is not strongly affected by the input power if $P_{rf} < -15$ dBm. The RF harvesters developed in this work are dedicated to collect power from -15 to -25 dBm. Over this range the diode model can be considered as stable, and the slight frequency shift is still covered by the antenna bandwidth.

B) Rectifier Characterization

The power efficiency and the power sensitivity are two conversion characteristics of importance in RF harvesters. However, the RF harvester operating at low power level accumulates the energy in a storage element, to further release it to the application. In such accumulation mode the power sensitivity becomes more important than the power efficiency.

For the characterization the rectifier is not connected to a load. The load represents the equivalent impedance of the application (clock, sensor) to power. The effectiveness of RF-DC conversion of the rectenna and its DC output voltage varies depending on the load value. The rectifier is first characterized in a single tone mode, 915 MHz and 2.44 GHz respectively, and then in a dual-band mode. Measurements of the unloaded rectified voltage versus various input power P_{rf} are reported in Figure 6.

Fig. 6: Unloaded rectified voltage for various input power

To compare the results of the two considered tones, the target is fixed to a value of 1V. In a single tone mode, the required P_{rf} to rectify 1V is close to -18 dBm at 915 MHz, and would be larger than -15 dBm at 2.44 GHz. In a dual-band mode the circuit only needs a power P_{rf} of -20 dBm at each frequency. The dual-band rectification significantly improves the power sensitivity. The reverse breakdown voltage of the HSMS285 Schottky diode limits the input power to -9 dBm, for which V_{rec} is 4,56 V.

III. ANTENNA DESIGN

To meet the low-cost constraints, the RF energy harvester will be implemented on a single low cost substrate, an FR4 PCB. For the antenna, there are more efficient substrates with a higher permittivity to reduce the size of the antenna or a lower losses but their cost is much higher than the improved performance. These powerful substrates fail to build low cost energy harvesters. This section exposes the design of two dual-band antennas implemented on a 1.6 mm FR4 printed circuit board. The fabrication uses a mechanical etching process with a 200 μ m resolution. We have chosen two complementary antenna topologies with a directional and omnidirectional radiation pattern.

A) Dual - band patch antenna

Emitting and receiving antennas do not usually meet the same constraints. Mobile devices such as smartphones and tablets use compact antennas (ifa, pifa...) to address the trade off between performance and size. Base stations can afford large efficient radiating elements (omnidirectional or directional antennas depending on the application). For energy harvesting purpose, micro-strip patch antennas are commonly used [15-17]. A rectangular micro-strip patch antenna (RMPA) is first developed to suit with both low cost technology of implementation and co-integration with the rectifier. Based on the cavity-model approximation, the resonant frequencies of the RMPA for the TM_{mn} mode is described in (1).

$$f_{mn} = \frac{c}{2\sqrt{\epsilon_r}} \sqrt{\left(\frac{m}{L}\right)^2 + \left(\frac{n}{W}\right)^2} \quad (1)$$

W, L are the patch dimensions, $c = 3 \cdot 10^8$ m/s

The antenna dimensions, 68 cm^2 ($8.8 \times 7.8 \text{ cm}$), described Fig.7a are dependent to the frequency bands and the feed location is selected to only excite the fundamental modes TM_{01} and TM_{10} . Those modes permit to obtain a large aspect ratio ($W/L = 2,7$) but reduce the performance of the RMPA. On the other hand, TM_{01} and TM_{30} modes require an aspect ratio close to one but offer beneficial radiation patterns for our application. The RMPA is fed by a probe whose position (x,y) adjusts the matching both at 915 MHz and 2.44 GHz. This two operating bands of the proposed antenna are on cross polarization planes. The geometric parameters of RMPA have been optimized with an approximate model, the TL model [18], and with a full wave method. Details of the two approaches have been studied in [19]. The return loss of the RMPA is better at 915 MHz than 2.44 GHz because the maximum impedance of TM_{30} mode is 31Ω [19]. The TM_{30} mode does not achieve 50Ω because it is not a fundamental mode. This antenna has a maximum gain of 1.3 dB at 915 MHz (Fig.7b) and 2.5 dB at 2.44 GHz (Fig.7c). This two operating bands of the proposed antenna are on cross polarization planes.

The realized gains of the dual band patch antenna are lower than the classical patch antenna because the radiating efficiency is low, 60% for the TM_{01} mode and 30% for the TM_{30} mode. The FR4 substrate has a loss tangent of 0.02. The radiation efficiency of the dual band patch antenna is highly dependent of the substrate losses.

Fig. 7. Layout of the RMPA antenna (a) - Radiation pattern at 915MHz (b) and 2.44 GHz (c)
Solid and dashed lines correspond to E-plane and H-plane respectively

B) Multi-band arm dipole antenna

The second antenna is a multi-band dipole type composed of three arms. Its dimension is about 23 cm^2 ($11.1 \times 2.1 \text{ cm}$), Fig.8a. Each arm is designed to work at one band of frequency. The longer one is for the 915 MHz, the middle one, not useful in our case, is for the 1.4 GHz and the last one, the smaller, is dedicated to 2.4 GHz [20].

All the geometric parameters have been optimized with a full-wave method in order to be matched both at 915/ 2440MHz. On Fig.6b and 6c, the radiation pattern is plotted for the elevation plane (orthogonal to substrate) of the simulated antenna. The maximum gain is 0.5 dB at 915 MHz and 3.4 dB at 2.44 GHz at 90° , on the substrate plane. The radiation efficiency is 99% at 915 MHz and 95% at 2.44 GHz.

Fig. 8. Layout of the multi-band arms dipole antenna (a) - Radiation pattern at 915 MHz (b) and 2.44 GHz (c). Solid and dashed lines correspond to E-plane and H-plane respectively

It is interesting to compare the characteristics and performances of the two types of antennas. Although the radiation efficiency of the dipole antenna is better than the patch antenna, the antenna gains are similar because the high directivity of the RMPA antenna compensates the low values of radiation efficiency. When there are no cost constraints, it is interesting to use high performance substrates for the design of RMPA antennas because they improve the radiation efficiency and consequently antenna gain.

Moreover, the integration of the antenna with the rectifier will not be made in the same way. Considering the patch antenna, the rectifier can be integrated on the ground plane allowing a more compact solution. The dipole antenna, which is ground plane free, is less sensitive to the surrounding environment in our case. The performance of the dipole antenna and especially the radiation efficiency are very weakly dependent of the substrate characteristics. The design of a dipole antenna can be easily reuse with other material such as Kapton®, paper, Plexiglas to name a few.

IV. WIRELESS POWER TRANSMISSION

This part presents the measurement results of the assembled RF harvesters in the context of Wireless Power transfer. The two dual-band harvesters are realized with COTS devices such as HSMS diodes and capacitors. Those elements are reported by heat-treating. The RF to DC converter board, including the matching network and the rectifier, is reported on the backside and connected to the radiation part, on the front side, through a via (Fig.9a). The dipole antenna is connected to the rectifier circuit using SMA connector (Fig.9b).

Fig. 9. Dual-band RF harvesters based on patch antenna (a) – arms dipole antenna (b)

For the dual-band RF harvester based on patch antenna, the return loss, S_{11} , is measured for an input power of -20 dBm with a HP8720 network analyser. The patch antenna, the rectifier and the dipole antenna are centered at 915 MHz and 2.44 GHz with a low return loss ($S_{11} < -15$ dB), Fig.10. The return loss of the RMPA antenna is better at 915 MHz than 2.44 GHz because the maximum impedance of TM30 mode is 31Ω (Fig. 6 and Fig. 7 of [16]). The TM30 mode does not achieve 50Ω because it is not a fundamental mode.

Fig. 10. Measured return loss S_{11} of the dual-band rectifier, patch and arms dipole antenna

A) Remote Powering and Power Efficiency

The rectenna is connected to a clock, which mimics a low power application. The remote powering of this clock is performed in a furnished room of the lab according the schematic of Fig.11. The distance between the source and the antenna is fixed to 2 m. The clock is turned on for different scenarios of transmitted power. For each combination of power proposed in Fig.12, the RF power is first measured with a calibrated antenna and a power meter. Then, the rectenna is measured and P_{eff} is the ration between the power delivered to the load (here the clock) and the power available at the antenna.

Fig. 11. Schematic and picture of the scene of remote powering of a clock

The power efficiency of the patch and the dipole rectenna is worked out from these experiments and reported in Fig.12. The power efficiency η is defined as the ratio between the DC power delivered to the clock and the RF power collected by the antenna.

Fig. 12. Power efficiency of the dual-band RF harvester based on the patch (a) and the arms dipole (b) antenna

The minimum power required to turn on the clock with the patch-based harvester, Fig. 10.a, is a two tone signal featuring: -19.5 dBm at 915 MHz and -20 dBm at 2.44 GHz. At this point, the power efficiency is 12.5 %, which corresponds to a DC output power of 2.7 μ W/1V.

A maximum efficiency of 24 % occurs for a combined power of -16.5 dBm at 915 MHz and -14 dBm at 2.44 GHz. The harvester is able to deliver a DC output power of 15 μ W. The harvester based on the arm dipole antenna needs a minimum power of -19.9 dBm at 915 MHz and -15 dBm at 2.44 GHz at the antenna to turn on the clock. For these conditions of remote powering, the efficiency of the harvester is 11 %. It delivers a DC power of 3.8 μ W/1.15 V. The maximum power efficiency, 15.5 %, yields for an input power of -14.4 dBm at 915 MHz and -9.7 dBm at 2.44 GHz, the DC output power is 21 μ W.

This scenario of remote powering figures out that the harvester based on the patch antenna exhibits a better power efficiency than the harvester combined with the dipole element. This difference is due to the antenna gains. Referring to Fig. 7 and Fig. 8, the gain of the patch antenna is larger (+0.8dB) at 915 MHz and lower (-0.9 dB) at 2.44 GHz than the dipole element. However the rectifier, referenced in [16], achieves a power efficiency of 17% at 915 MHz and only 5% at 2.44 GHz for an input signal of -15 dBm. As consequences the patch-based harvester is able to extract more power from a 915 MHz signal than the dipole-based harvester can do at 2.44 GHz. For this reason the overall efficiency of the patch harvester is better.

B) Power Sensitivity

The power sensitivity is measured with the same scenario of Fig.11 but the clock is disconnected. The output voltage is reported for different combination of collectable power at the antenna in a dual-band configuration.

Fig. 13. Rectified voltage of the RF harvester based on patch (a) and arm dipole (b) antenna

To rectify a 1V DC voltage, the patch-based harvester, Fig.13a, requires a two dual-band configuration: -19.5 dBm at 915 MHz and -25 dBm at 2.44 GHz, which is equivalent to an input power of -18.4 dBm (or 14 μ W). For the same purpose the dipole-based harvester, Fig.13b, needs a dual-tone of -22.1 dBm at 915 MHz and -17.8 dBm at 2.44 GHz. The equivalent input power of this 2-tone signal is -16.5 dBm (or 22 μ W). The patch-based harvester exhibits a better sensitivity than the dipole harvester for the same reason exposed in the part A of this section. In Fig.6, which reports the power sensitivity of the rectifier part only, the overall sensitivity is almost the same for the dipole harvester. It is improved by 1.8 dB for the patch harvester due to the additional gain of the antenna at 915 MHz.

C) Discussion and Comparison with the state of the art

An important characteristic of a remote powered device is its size. Indeed it is expected to be as small as possible to make it unobtrusive to our closest environment. In a scenario of RF harvesting the antenna footprint determines the compactness of a harvester operating Ultra High Frequency (UHF) bands. To complete the comparison between the two harvesting modules developed in this work, two figures of merit, FOM_{sens} and FOM_{eff} , including the size of the antenna, are proposed in (2) and (3).

$$FOM_{sens} = \frac{V_{REC@Psens}(V)}{\frac{P_{sens}(\mu W)}{100\mu W} \cdot \frac{A_{ant}(cm^2)}{100cm^2}} \quad (2)$$

With: P_{sens} the input RF power required to provide $V_{REC@Psens}$ the unloaded rectified output DC voltage, and A_{ant} the area of the antenna.

$$FOM_{eff} = \frac{\eta(\%)}{\frac{P_{eff}(\mu W)}{100\mu W} \cdot \frac{A_{ant}(cm^2)}{100cm^2}} \quad (3)$$

With: P_{eff} the input RF power required to achieve η the overall power efficiency.

FOM_{sens} and FOM_{eff} do not represent the same scenario of application. The FOM_{sens} illustrates the capability of the rectenna to start collecting energy and store it in an element such as a capacitor or a battery to further release it. FOM_{eff} demonstrates the capability of the RF harvester to yield “on time powering”: the rectenna is connected to an application and

supply it on time. Both are reported in the Table I, which also includes some references of the state of the art. The ability of the proposed rectenna to simultaneously operate in two frequency bands, significantly improves the power sensitivity.

Table I. Comparison with the state of the art

Ref.	Freq (GHz)	Efficiency (% $@P_{rf}$)	Sensitivity ($V_{rec}@Prf$)	Number of stage	Schottky diodes	Size (cm^2)	FOM Sens	FOM Eff
[21]	0.9	15% @ -10dBm	0.75V @ -10dBm	1	SMS-7630	15×15	1.9	6.6
[21]	2.4	9% @ -13dBm	0.9V @ -13dBm	1	SMS-7630	15×15	1.25	8
[22]	2.45	10.5% @ -20dBm	0.075V @ -20dBm	1	SMS-7630	3.4×3.4	6.5	905
[23]	0.915/ 2.45	14% @ -20/-20	0.36V @ -10/-10	1	SMS-7630	6×6	0.5	185
[24]	1.8/2.2 /2.5	55% @ -10dBm	300mV @ -32dBm 3tones	1	SMS-7630	7×7	20	112
This work Dipole	0.915/ 2.44	11% @ -20/-15dBm	1V @ -22/-18dBm	4	HSMS- 2850	2.1×11	19.8	136
This work Patch	0.915/ 2.44	12.5% @ -19.5 dBm/ -20dBm	1V @ -19.5dBm/ -25dBm	4	HSMS- 2850	7.8×8.8	10.5	100

According the Table I, the patch-based harvester exhibits the highest sensitivity to rectify 1V with a dual-tone featuring: -19.5 dBm at 915 MHz and only -25 dBm at 2440 MHz. The FOM_{sens} represents the trade-off between the sensitivity performances of a rectenna and the antenna area. The FOM_{eff} rates the efficiency performances to the antenna area. For these two figures of merit, the rectenna based on the multi-arm dipole element yields the best trade-off, both for FOM_{sens} and FOM_{eff} , compared to the patch-based solution. This dual tone and multi-arm dipole harvester is close to the work proposed in [24] which exhibits the highest FOM_{sens} reported so far in the literature to our knowledge.

V. CONCLUSION

The range of power collectable in a scenario of RF harvesting varies from -15dBm to -25dBm. To address this purpose the rectenna proposed in this work are optimized to operate at a RF input power close to -20 dBm (or 10 μ W). To further improve the ability to collect the RF energy, these rectenna, developed with Schottky diodes HSMS285 from Avago, perform a concurrent harvesting in the 915 MHz and 2.44 GHz ISM bands. The harvester including a patch antenna implemented on a 1.6mm FR4 PCB achieves the highest sensitivity. It provides a 1V-rectified voltage for a dual-tone excitation of -19.5 dBm at 915 MHz and -25 dBm at 2.44 GHz. For these conditions of operation the rectenna yields a power efficiency of 12.5%. To take into account the dimensions of the haverster, two figures of merit, FOM_{sens} and FOM_{eff} including the size of the antenna, respectively related to the power sensitivity and the power efficiency are proposed. The rectenna developed with the arm dipole element exhibits the highest figures of merit. A case of application is proposed with the remote powering of a

digital clock consuming $1\text{V}/5\mu\text{A}$. The patch based harvester turns on the device with a dual tone excitation at the antenna of -19.5 dBm at 915 MHz and -20 dBm at 2.44 GHz . For the same scenario the harvester connected to the multi-arm dipole element needs a power of -22.1 dBm at 915 MHz and -17.8 dBm at 2.44 GHz .

REFERENCES

- [1] T. Paing, A. Dolgov, J. Shin, J. Morroni, J. Brannan, R. Zane, and Z. Popovic, "Wirelessly powered wireless sensor platform" in Eur. Microw. Conf. Dig, Munich, Germany, Oct. 2007, pp. 241-244.
- [2] J. Bernhard, K. Hietpas, E. George, D. Kuchima, and H. Reis, "An interdisciplinary effort to develop a wireless embedded sensor system to monitor and assess corrosion in the tendons of pre-stressed concrete girders," in Proc. IEEE Top. Conf. Wireless Commun, 2003, pp. 241-243.
- [3] C. Walsh, S. Rondineau, M. Jankovic, G. Zhao, and Z. Popovic, "A conformal 10-GHz rectenna for wireless powering of piezoelectric sensor electronics," in IEEE MTT-S Int. Microw. Symp. Dig, Jun. 2005, pp. 143-146.
- [4] X. Zhao, T. Qian, G. Mei, C. Kwan, R. Zane, C. Walsh, T. Paing, and Z. Popovic, "Active health monitoring of an aircraft wing with an embedded piezoelectric sensor/actuator network," Smart Mater. Struct, vol. 16, no. 2007, Jun. 2007, pp. 1218-1225.
- [5] K. Lin, J. Yu, J. Hsu, S. Zahedi, D. Lee, J. Friedman, A. Kansal, V. Raghunathan, and M. Srivastava, "Helimote: Enabling long-lived sensor networks through solar energy harvesting," in 3rd Int. Conf. Embedded Networked Sensor Syst., Nov. 2005, p. 309.
- [6] J.A. Paradiso and T. Starner, "Energy scavenging for mobile and wireless electronics," IEEE Pervasive Computing, Vol. 4, and Issue: 1, Jan-March 2005, pp. 18- 27.
- [7] K. R. Foster, "A world awash with wireless devices", IEEE Microwave magazine, vol. 14, Issue 2, March 2013, pp. 73-84.
- [8] T. Le, K. Mayaram, and T. Fiez, "Efficient far-field radio frequency energy harvesting for passively powered sensor networks," IEEE J. Solid-State Circuits, vol. 43, no. 5, May 2008, pp. 1287-1302.
- [9] J. Hirai, T.W. Kim, and A. Kawamura, "Wireless transmission of power and information for cableless linear motor drive," IEEE Trans. Power Electron, vol. 15, 2000, pp. 21-27.
- [10] H. Nishimoto, Y. Kawahara, and T. Asami, "Prototype implementation of ambient RF energy harvesting wireless sensor networks," IEEE Sens. J., Nov. 2010, pp. 1282-1287.
- [11] BN. Shinohara, "Power without wires," IEEE Microw. Mag, vol. 12, no. 7, Dec. 2011, pp. S64-S73.

- [12] M. Pinuela, P.D. Mitcheson, S. Lucyszyn, "Ambient RF Energy Harvesting in Urban and Semi-Urban Environments", IEEE Trans. On Microwave Theory and Techniques, vol. 61, N°7, July 2013.
- [13] Simon Hemour, Ke Wu "Radio-Frequency Rectifier for Electromagnetic Energy Harvesting : Developement Path and Future Outlook", Proceeding of the IEEE, Vol.102, No.11, November 2014.
- [14] T. Taris, L.Fadel, L.Oyhenart, V. Vigneras, "COTS-Based Modules for Far-Field Radio Frequency ", IEEE NEWCAS, Paris, France, June 2013, pp. 1-4.
- [15] Sika Shrestha, Sun-Kuk Noh, and Dong-You Choi, « Comparative Study of Antenna Designs for RF Energy Harvesting » International Journal of Antennas and Propagation Volume 2013, 10 pages.
- [16] Z. W. Sim, R. Shuttleworth, M. J. Alexander, B. D. Grieve, « Compact patch antenna design for outdoor RF energy harvesting in wireless sensor networks, Progress In Electromagnetics Research, Vol. 105, 273–294, 2010.
- [17] Naimul Hasan, Santu Kumar Giri, « Design of low power RF to DC generator for energy harvesting application », International Journal of Applied Sciences and Engineering Research, Vol 1, Issue 4, 2012.
- [18] H. J. Visser, "Approximate Antenna Analysis for CAD", Wiley, 2009.
- [19] R. Berges, L.Fadel, L. Oyhenart, V. Vigneras, T. Taris, "A dual Band 915MHz/2.44GHz RF Energy Harvester", EUMW, Paris France, Sept 2015.
- [20] Y-Y.Lu, J. Guo, H-C. Huang, "Design of Triple Symmetric Arms Dipole Antenna for 900/1800/2450MHz Applications", Conf on Intelligent Information Hiding and Multimedia Signal Processing", 2014.
- [21] D. Masotti, A. Costanzo, M. Del Prete, V. Rizzoli, "Genetic-based design of a tetra-band high-efficiency radio-frequency energy harvesting system," IET Microwaves, Antennas Propagation, vol.7, no. 15, June 2013, pp. 1254-1263.
- [22] G. Vera, A. Georgiadis, A. Collado, and S. Via, "Design of a 2.45GHz rectenna for electromagnetic (EM) energy scavenging", Proc. IEEE Radio and Wireless Symp, 2010, pp. 61-64.
- [23] K. Niotaki, S. Kim, S. Jeong, A. Collado, A. Georgiadis, and M. Tentzeris, "A compact dual-band rectenna using slot-loaded dual band folded dipole antenna," IEEE Antennas and Wireless Propagation. Lett. vol. 12, pp. 1634–1637, 2013.
- [24] C. Song, Y. Huang, J. Zhou, J. Zhang, S. Yuan, and P. Carter, "A High-efficiency Broadband Rectenna for Ambient Wireless Energy Harvesting", IEEE Transactions on Antennas and Propagation, accepted May 2015.

Bibliographies

Ludivine FADEL received the Ph.D in electrical engineering from the University of Bordeaux, France, in 2004. She is an Associate Professor at Bordeaux University and her main research interests include wireless power transfer and energy harvesting, materials and printing technologies for RF application.

Laurent Oyhenart received the Ph.D. degree in electrical engineering from the University of Bordeaux, Bordeaux, France, in 2005. He is currently an Associate Professor with the University of Bordeaux and develops his research activities in the IMS laboratory. His research interests include computational electromagnetics, photonic crystals and antenna synthesis.

Romain Bergès is a PhD student at IMS Laboratory. He received his Master from Bordeaux University in Electronic, in 2014. His current research focuses on RF Energy Harvesting.

Valérie Vignerat is a full professor in the Polytechnic Institute of Bordeaux and conducts research in the IMS Laboratory on complex structures (mixtures, structured media, self-assembled media) both by simulation to predict or optimize their properties and by characterization before their integration in high frequency systems (antennas, electromagnetic compatibility, radar shieldness...).

Thierry Taris is a full professor at the Bordeaux Institute of Technology (Bx-INP). He joined the IMS lab in 2005 where his research interests are related to the Radio-frequency Integrated Circuits in Silicon technologies.

List of figures and tables

Fig. 1: Schematic of a Wireless RF Power Transmission (WPT) system.

Fig. 2: Architecture of the RF to DC converter.

Fig. 3: Topology of the input-matching network.

Fig. 4: Equivalent model of the RF to DC converter, 915 MHz (a) - 2,44 GHz (b).

Fig. 5: Measured S_{11} of a 4-stage voltage multiplier with a L section at 900 MHz for various input power P_{rf} .

Fig. 6: Unloaded rectified voltage for various input power.

Fig. 7: Layout of the RMPA antenna (a) - Radiation pattern at 915MHz (b) and 2.44 GHz (c) Solid and dashed lines correspond to E-plane and H-plane respectively.

Fig. 8: Layout of the multi-band arms dipole antenna (a) - Radiation pattern at 915 MHz (b) and 2.44 GHz (c). Solid and dashed lines correspond to E-plane and H-plane respectively.

Fig. 9: Dual-band RF harvesters based on patch antenna (a) – arms dipole antenna (b).

Fig. 10: Measured return loss S_{11} of the dual-band rectifier, patch and arms dipole antenna.

Fig. 11: Schematic and picture of the scene of remote powering of a clock.

Fig. 12: Power efficiency of the dual-band RF harvester based on the patch (a) and the arms dipole (b) antenna.

Fig. 13: Rectified voltage of the RF harvester based on patch (a) and arm dipole (b) antenna.

Table I. Comparison with the state of the art.